



220 - 415V Diesel



Rating Range

		KH550
		50Hz
Standby	kW	437
	kVA	546
Prime	kW	400
	kVA	500



Standard Feature:

- KOHLER Co., provides one-source responsibility for the generating system and accessories
- The generator set and it's components are prototypetested, factory-built and production-tested
- One-year standard warranty covers all systems and components
- Doosan engine with 27.5 volt battery charging alternator
- Meccalte single bearing alternator class H insulation system
- Unit-mounted radiator with 40°C (104°F) ambient air capability
- Skid and vibration isolators
- Dry type air filter
- Main circuit breaker
- Microprocessor controller
- Battery, battery rack and cables
- · Operation and installation manual

Generator Rating

				Stand	lby	Prim	ne
Alternator	V	Phs	Hz	kW/kVA	Amps	kW/kVA	Amps
	220/380	3	50	437/546	830	400/500	760
ECO40 3S4B	230/400	3	50	437/546	788	400/500	722
	240/415	3	50	437/546	760	400/500	696

RATINGS: All three-phase units are rated at 0.8 power factor. PRP: Prime power is available for an unlimited number of annual operating hours in variable load applications in accordance with ISO8528.1. A 10% overload capability is available for a period of 1 hours within a 12-hour period of operating in accordance with ISO3046.1. ESP: The emergency standby power rating is applicable for supplying emergency power in variable load applications in accordance with ISO-8528.1. Overload is not allowed

The generator set manufacturer reserves the rights to change the design or specification without notice and without any obligation or liability whatsoever

Alternator Specification

•	IEC60034, NEMA MG1.22, ISO8528, CSA, UL,
	ISO9001,ISO14001, CE standard
•	IP23

Class H Insulation

2/3 winding pitch

Specification	50Hz
Voltage	400V
Standby (27°C),kVA	546
Prime (40°C), kVA	500
Efficiency (full load)	94.6%
Air Flow, m^3/min	54
Direct-axis (X"d), %	11.8
	_

Specification	Alternator
Manufacturer	MECC ALTE
Туре	4 Pole Rotating
Leads	12 Leads
Voltage regulator	DER-1
Insulation:	NEMA MG1
Material	Class H
Coupling	Single Bearing
Voltage regulation	±1%

Specification

Engine		Engine Electrical	
Engine Specification		Engine Electrical	
Manufacturer	Doosan/Hyundai	Battery Charging	27.5V
Engine Model	DP158LD	Ground/Negative	Negative
Engine Type	4cycle,Turbocharge	Voltage (DC)	27.5
Cylinder arrangement	8V	Starter motor rated voltage (DC)	24
Displacement, L (in3)	14.62 (892)	Battery, recommended Ampere	
Bore and Stoke, mm (in)	128 x 142 (5.0 x 5.6)	Hour (CCA)	
Compression ratio	15:1	QTY, CCA	2,170
Piston speed, m/min (ft/min)	426 (1398)	Battery Voltage (DC)	12
Rated speed (r/min)	1500		
Max, power at rated rpm, kW (BHP)	510 (684)	Fuel	
Governor Type	Electronic	Fuel System	
Frequency Regulation	±0.5%	Max. Fuel Flow, Lph (gph)	315 (83.2)
Air Cleaner Type	Dry	Fuel prime pump	Manual
		Fuel Type	Diesel
Exhaust		_ Fuel Tank Capacity, L (gal)	500 (132)
Exhaust System		_	
Exhaust manifold type	Dry	Lubrication	
Exhaust Flow, m^3/min (cfm)	98 (3459)	Lubrication System	
Exhaust Temperature, °C (°F)	561 (1042)	Туре	Full Pressure
Max allowable back pressure, kPa (in Hg)	5.9 (1.74)	Oil pan capacity with filter, L (qt)	22 (23.3)

RATINGS: All three-phase units are rated at 0.8 power factor. PRP: Prime power is available for an unlimited number of annual operating hours in variable load applications in accordance with ISO8528.1. A 10% overload capability is available for a period of 1 hours within a 12-hour period of operating in accordance with ISO3046.1. ESP: The emergency standby power rating is applicable for supplying emergency power in variable load applications in accordance with ISO-8528.1. Overload is not allowed The generator set manufacturer reserves the rights to change the design or specification without notice and without any obligation or liability whatsoever

Specification

Cooling

Radiator System	
Radiator Ambient Temperature, °C (°F)	40 (104)
Radiator system capacity , L (gal)	79 (20.9)
Heat rejected to cooling water at rated, kW (Btu/min)	226 (12852)
Water pump type	Centrifugal
Fan loss, kW (HP)	16 (21.4)
Max, restriction of cooling air, intake and discharge of radiator, kPA (in H_2O)	-

Air requirement	
Radiator-cooled cooling air m^3/min (scfm)	700 (24720)
Combustion air, m^3/min (ft^3/min)	33.1 (1186)
Air density =1.20 kg/m^3 (0.075 lb/ft^3)	

Fuel Consumption	
Diesel, L/h (gal/h), load%	Standby
100%	127.8 (33.8)
Diesel, L/h (gal/h), load%	Prime
100%	115.1 (30.4)
75%	83.4 (22)
50%	55.1 (14.6)

Controller



The APM403 is a versatile control unit which allows operation in manual or automatic mode

- Measurements: voltage and current
- kW/kWh/kVA power meters
- Standard specifications: Voltmeter, Frequency meter.
- J1939 CAN ECU engine control
- Alarms and faults: Oil pressure, Coolant temperature,
- Overspeed, Start-up failure, alternator min/max,
- Emergency stop button.
- Engine parameters: Fuel level, hour counter
- Event log/ Management of the last 300 genset events.
- · Mains and genset protection
- Clock management
- USB connections, USB Host and PC,
- Communications: RS485 INTERFACE
- ModBUS protocol /SNMP

RATINGS: All three-phase units are rated at 0.8 power factor. PRP: Prime power is available for an unlimited number of annual operating hours in variable load applications in accordance with ISO8528.1. A 10% overload capability is available for a period of 1 hours within a 12-hour period of operating in accordance with ISO3046.1. ESP: The emergency standby power rating is applicable for supplying emergency power in variable load applications in accordance with ISO-8528.1. Overload is not allowed

The generator set manufacturer reserves the rights to change the design or specification without notice and without any obligation or liability whatsoever



KOHLER CO., Kohler, Wisconsin 53044 USA Phone +1 (920)-565-3381 Kohler Power.com KOHLER Power Systems 400 1808 900 Power@kohler.com

Option

Cooling system

- Block heater (recommend to use when below 0°C (32°F)
- Radiator core guard

Fuel system

- Automatic fuel tank fil kit
- Fuel tank with secondary containment basin
- Subbase fuel tank leak alarm
- Water separator fuel filter

Electrical System

- Battery charger, equalize/float type
- Battery isolator switch

Engine and alternator

- Alternator strip heater
- Air cleaner, heavy duty (with air restriction indicator)
- Droop kit with 3-function voltage regulator
- Electronic governor
- Lube oil drain pump
- · PMG alternator and voltage regulator
- Tropical heavy-duty alternator insulation

Others

- _____
- •
- -----
- · -----
- _____
- •

Dimension and weight

Open Model



Dimension, LxWxH mm: 3470 x 1500 x 1813

Dry weight, kg: 3390 Wet weight, kg: 3890

RATINGS: All three-phase units are rated at 0.8 power factor. PRP: Prime power is available for an unlimited number of annual operating hours in variable load applications in accordance with ISO8528.1. A 10% overload capability is available for a period of 1 hours within a 12-hour period of operating in accordance with ISO3046.1. ESP: The emergency standby power rating is applicable for supplying emergency power in variable load applications in accordance with ISO-8528.1. Overload is not allowed

The generator set manufacturer reserves the rights to change the design or specification without notice and without any obligation or liability whatsoever